



3LED LIGHTHEAD

(E-Mark Approval)

Features

- Operate Voltage 10~30 VDC
- 13 Flash Patterns

Operating Instruction

- Connect **RED** wire to +VDC – Fuse @1A.
- Connect **BLACK** wire to chassis ground.
- Connect **BLUE** wire to **BLACK** wire momentarily to select next flash pattern.
- Connect **BLUE** wire to **BLACK** wire for more than 5 sec. to turn off the unit.

Synchronised Flash

Connect **YELLOW** wires of all units together and set all units to that synchronised flash.

Alternate Flash

Connect **YELLOW** wires of all units together and set all units to either phase 1 or phase 2 of that alternate flash. Units set on phase 1 will alternate with units set on phase 2.

Flash Patterns:

PA1	ECE R65 120FPM Single Flash ph1 (DEFAULT)
PA2	ECE R65 120FPM Single Flash ph2
PA3	ECE R65 120FPM Double Flash ph1
PA4	ECE R65 120FPM Double Flash ph2
PA5	ECE R65 120FPM Quad Flash ph1
PA6	ECE R65 120FPM Quad Flash ph2
PA7	Single Flash 75FPM ph1
PA8	Single Flash 75FPM ph2
PA9	Double Flash 75FPM ph1
PA10	Double Flash 75FPM ph2
PA11	Quad Flash 75FPM ph1
PA12	Quad Flash 75FPM ph2
PA13	Off